

**MAGNETIC STARTERS & TRANSFORMERS (IF REQUIRED) FOR  
STANDARD HYTROL MOTORS**

**FOOT MOUNTED 115 /230 VOLT 1 PHASE (1.15 S.F.)**

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL.	VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER

30.2014 C56H1502 FB56 B-3622-13	27# M-8275 610301-598 416820-30	1/2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	NOT	NOT
			9	REV. ER-1SC10	33.4161 AB107HNX2	AB140MC2EC10	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SB63	33.4121 AB103HNX2	33.4341 4.0-6.3 AMPS	33.1911	33.1691
			4.5	REV. ER-2SB63	33.4181 AB107HNX3	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20

30.3014 C56H1501 FB56 B-3622-13	31# M-6983 610301-598 416820-30	3/4 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC16	33.4121 AB103HNX2	33.4381 10-16 AMPS	NOT	NOT
			11	REV. ER-1SC16	33.4161 AB107HNX2	AB140C2EC16	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SB63	33.4121 AB103HNX2	33.4341 4.0-6.3 AMPS	33.1911	33.1691
			5.5	REV. ER-2SB63	33.4181 AB107HNX3	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20

30.4014 C56H1774 FC56 B-3622-13	35# M-8274 610301-598 416820-30	1 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC16	33.4121 AB103HNX2	33.4381 10-16 AMPS	NOT	NOT
			13.6	REV. ER-1SC16	33.4161 AB107HNX2	AB140C2EC16	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			6.8	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20

30.5014 C14H1501 FE145T B-3622-13	46# M-3145 610301-602 416820-30	1 1/2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC20	33.4121 AB103HNX2	33.4401 16-20 AMPS	NOT	NOT
			16.0	REV. ER-1SC20	33.4161 AB107HNX2	AB140MC2EC20	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			8.0	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20

30.60141 C14H1505 FE145T B-3622-13	54# M-6626 610301-602 416820-30	2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC20	33.4121 AB103HNX2	33.4401 16-20 AMPS	NOT	NOT
			16.0	REV. ER-1SC20	33.4161 AB107HNX2	AB140MC2EC20	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			8.0	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20

**FOR MODELS A & R ONLY 115 / 230 VOLT SINGLE PHASE (50 Hz RENAMEPLATED TO 60 Hz) (1.0 S.F.)**

30.2016 E79B6458 FB56 B-3622-13	29# M-2672 610302-393 416820-30	1/2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	NOT	NOT
			6.8	REV. ER-1SC10	33.4161 AB107HNX2	AB140MC2EC10	REQUIRED	REQUIRED
			230 / 1 / 60	NON-REV EN-2SB63	33.4121 AB103HNX2	33.4341 4.0-6.3 AMPS	33.1911	33.1691
			3.4	REV. ER-2SB63	33.4181 AB107HNX3	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20

NOTE:

Each Magnetic Starter (EXECPT 115 VOLT) Shall Be Supplied, As Standard, With A Control Circuit Transformer,  
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)