

**MAGNETIC STARTERS & TRANSFORMERS FOR
STANDARD HYTROL MOTORS**

C-FACE OR FOOT MOUNTED 200-208 / 400-416 VOLT 3 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL.	VOLTAGE F.L.AMPS VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
30.8154 P56H1020 FE56C B-3622-13	23# M4702.200 610302-299 416820-1	1/2 1725 TEFC	200-208/3/60	NON-REV EN-20B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1910	33.1691
			2.5	REV ER-20B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N3PHYH	AB140MCASA20
			400-416/3/60	NON-REV EN-40B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	NOT	33.1691
			1.25	REV ER-40B16	33.4141 AB107HNX1	AB140MC2EB16	STOCKED	AB140MCASA20
30.8254 P56H1019 EC56C B-3622-13	27# M4701.200 610301-226 416820-1	3/4 1725 TEFC	200-208/3/60	NON-REV EN-20B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1910	33.1691
			3.2	REV ER-20B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N3PHYH	AB140MCASA20
			400-416/3/60	NON-REV EN-40B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	NOT	33.1691
			1.6	REV ER-40B16	33.4141 AB107HNX1	AB140MC2EB16	STOCKED	AB140MCASA20
30.8354 P56H1178 EB56C B-3622-13	24# M7027.200 610301-226 416820-1	1 1725 TEFC	200-208/3/60	NON-REV EN-20B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1910	33.1691
			3.9	REV ER-20B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N3PHYH	AB140MCASA20
			400-416/3/60	NON-REV EN-40B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	NOT	33.1691
			1.95	REV ER-40B25	33.4141 AB107HNX1	AB140MC2EB25	STOCKED	AB140MCASA20
30.8454 P14H1120 FJ145TC B-3622-13	30# M2920.200 610301-264 416820-1	1 1/2 1725 TEFC	200-208/3/60	NON-REV EN-20B63	33.4101 AB103HNX1	33.4341 4.0-6.3 AMP	33.1910	33.1691
			6.5	REV ER-20B63	33.4141 AB107HNX1	AB140MC2EB63	AB1497N3PHYH	AB140MCASA20
			400-416/3/60	NON-REV EN-40B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	NOT	33.1691
			3.25	REV ER-40B40	33.4141 AB107HNX1	AB140MC2EB40	STOCKED	AB140MCASA20
30.85341 P14H1119 FJ145TC B-3622-13	37# M2916.200 610301-264 416820-1	2 1725 TEFC	200-208/3/60	NON-REV EN-20C10	33.4101 AB103HNX1	33.4361 6.3-10.0 AMP	33.1910	33.1691
			7.2	REV ER-20BC10	33.4141 AB107HNX1	AB140MC2EC10	AB1497N3PHYH	AB140MCASA20
			400-416/3/60	NON-REV EN-40B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	NOT	33.1691
			3.6	REV ER-40B40	33.4141 AB107HNX1	AB140MC2EB40	STOCKED	AB140MCASA20

NOTE:

Each Magnetic Starter Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)