

**MAGNETIC STARTERS & TRANSFORMERS FOR
STANDARD HYTROL MOTORS**

C-FACE EASY CLEAN 230 / 460 VOLT 3 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL	VOLTAGE F.L.AMPS VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
30.861 P56H4515 FB56C B-3622-13	31# M6976-V 600763-98 416820-1	1/2 1725 NVEZ	230/3/60	NON-REV EN-23B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	33.1911	33.1691
			2.2	REV. ER-23B25	33.4141 AB107HNX1	AB140MC2EB25	AB1497N2PHYA	AB140MCASA20
			460/3/60	NON-REV EN-46B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1912	33.1691
			1.1	REV. ER-46B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYB	AB140MCASA20
30.862 P56H4516 FB56C B-3622-13	35# M8223-V 600763-98 416820-1	3/4 1725 NVEZ	230/3/60	NON-REV EN-23B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	33.1911	33.1691
			2.2	REV. ER-23B25	33.4141 AB107HNX1	AB140MC2EB25	AB1497N2PHYA	AB140MCASA20
			460/3/60	NON-REV EN-46B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1912	33.1691
			1.1	REV. ER-46B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYB	AB140MCASA20
30.863 P56H4517 FC56C B-3622-13	36# M8222-V 600763-98 416820-1	1 1725 NVEZ	230/3/60	NON-REV EN-23B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1911	33.1691
			2.8	REV. ER-23B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N2PHYA	AB140MCASA20
			460/3/60	NON-REV EN-46B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1912	33.1691
			1.4	REV. ER-46B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYB	AB140MCASA20
30.864 P14H4541 FJ145TC B-3622-13	40# M6915M-V 600763-100 416820-1	1 1/2 1725 NVEZ	230/3/60	NON-REV EN-23B63	33.4101 AB103HNX1	33.4341 4.0-6.3 AMP	33.1911	33.1691
			4.4	REV. ER-23B63	33.4141 AB107HNX1	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20
			460/3/60	NON-REV EN-46B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	33.1912	33.1691
			2.2	REV. ER-46B25	33.4141 AB107HNX1	AB140MC2EB25	AB1497N2PHYB	AB140MCASA20
30.865 P14H4515 FJ145TC B-3622-13	46# M2916-V 600763-96 416820-1	2 1725 EZFC	230/3/60	NON-REV EN-23C10	33.4101 AB103HNX1	33.4361 6.3-10.0 AMP	33.1911	33.1691
			6.4	REV. ER-23C10	33.4141 AB107HNX1	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20
			460/3/60	NON-REV EN-46B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1912	33.1691
			3.2	REV. ER-46B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N2PHYB	AB140MCASA20

NOTE:

Each Magnetic Starter Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)