

**MAGNETIC STARTERS & TRANSFORMERS FOR
STANDARD HYTROL MOTORS**

C-FACE ENERGY EFFICIENT 230 / 460 VOLT 3 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL	VOLTAGE F.L.AMPS VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
32.351 P56X1526 FB56C B-3622-13	26# M8006	1/2 1725	230/3/60	NON-REV EN-23B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1911	33.1691
	610302-817		460/3/60	REV. ER-23B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYA	AB140MCASA20
	416820-133	TENV-XE	0.75	NON-REV EN-46B10	33.4101 AB103HNX1	33.4261 0.63-1.0 AMP	33.1912	33.1691
				REV. ER-46B10	33.4141 AB107HNX1	AB140MC2EB10	AB1497N2PHYB	AB140MCASA20
32.352 P56X1529 FC56C B-3622-13	29# M8007	3/4 1725	230/3/60	NON-REV EN-23B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	33.1911	33.1691
	610302-817		460/3/60	REV. ER-23B25	33.4141 AB107HNX1	AB140MC2EB25	AB1497N2PHYA	AB140MCASA20
	416820-133	TENV-XE	1.1	NON-REV EN-46B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1912	33.1691
				REV. ER-46B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYB	AB140MCASA20
32.353 P56X1531 FC56C B-3622-13	31# M8218	1 1725	230/3/60	NON-REV EN-23B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1911	33.1691
	610302-817		460/3/60	REV. ER-23B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N2PHYA	AB140MCASA20
	416820-133	TENV-XE	1.4	NON-REV EN-46B16	33.4101 AB103HNX1	33.4281 1.0-1.6 AMP	33.1912	33.1691
				REV. ER-46B16	33.4141 AB107HNX1	AB140MC2EB16	AB1497N2PHYB	AB140MCASA20
32.354 P14X1485 FD145TC B-3622-13	38# M8216	1 1/2 1725	230/3/60	NON-REV EN-23B63	33.4101 AB103HNX1	33.4341 4.0-6.3 AMP	33.1911	33.1691
	610301-601		460/3/60	REV. ER-23B63	33.4141 AB107HNX1	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20
	416820-133	TEFC-XE	2.1	NON-REV EN-46B25	33.4101 AB103HNX1	33.4301 1.6-2.5 AMP	33.1912	33.1691
				REV. ER-46B25	33.4141 AB107HNX1	AB140MC2EB25	AB1497N2PHYB	AB140MCASA20
32.355 P14X1487 FE145TC B-3622-13	49# M4634H	2 1725	230/3/60	NON-REV EN-23B63	33.4101 AB103HNX1	33.4341 4.0-6.3 AMP	33.1911	33.1691
	610301-601		460/3/60	REV. ER-23B63	33.4141 AB107HNX1	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20
	416820-133	TEFC-XE	2.7	NON-REV EN-46B40	33.4101 AB103HNX1	33.4321 2.5-4.0 AMP	33.1912	33.1691
				REV. ER-46B40	33.4141 AB107HNX1	AB140MC2EB40	AB1497N2PHYB	AB140MCASA20

NOTE:

Each Magnetic Starter Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)