

**MAGNETIC STARTERS & TRANSFORMERS FOR
STANDARD HYTROL MOTORS**

FOOT MOUNTED 230 / 460 VOLT 3 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL.	VOLTAGE F.L.AMPS VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
30.2034 P56H5068 ED56 B-3622-13	24# M6904 610301-567 416820-133	1/2 1725 TEFC	230/3/60	NON-REV EN-23B25 REV. ER-23B25	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4301 1.6-2.5 AMP AB140MC2EB25	33.1911 AB1497N2PHYA	33.1691 AB140MCASA20
			460/3/60	NON-REV EN-46B16 REV. ER-46B16	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4281 1.0-1.6 AMP AB140MC2EB16	33.1912 AB1497N2PHYB	33.1691 AB140MCASA20
30.3044 P56H1301 EB56 B-3622-13	27# M4701M 610301-598 416820-133	3/4 1725 TEFC	230/3/60	NON-REV EN-23B40 REV. ER-23B40	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4321 2.5-4.0 AMP AB140MC2EB40	33.1911 AB1497N2PHYA	33.1691 AB140MCASA20
			460/3/60	NON-REV EN-46B16 REV. ER-46B16	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4281 1.0-1.6 AMP AB140MC2EB16	33.1912 AB1497N2PHYB	33.1691 AB140MCASA20
30.4044 P56H1437 ED56 B-3622-13	27# M6906D 610301-567 416820-133	1 1725 TEFC	230/3/60	NON-REV EN-23B40 REV. ER-23B40	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4321 2.5-4.0 AMP AB140MC2EB40	33.1911 AB1497N2PHYA	33.1691 AB140MCASA20
			460/3/60	NON-REV EN-46B25 REV. ER-46B25	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4301 1.6-2.5 AMP AB140MC2EB25	33.1912 AB1497N2PHYB	33.1691 AB140MCASA20
30.5034 P14G9244 FD145T B-3622-13	37# M8061-V 610301-600 416820-133	1 1/2 1725 TEFC	230/3/60	NON-REV EN-23B63 REV. ER-23B63	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4341 4.0-6.3 AMP AB140MC2EB63	33.1911 AB1497N2PHYA	33.1691 AB140MCASA20
			460/3/60	NON-REV EN-46B40 REV. ER-46B40	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4321 2.5-4.0 AMP AB140MC2EB40	33.1912 AB1497N2PHYB	33.1691 AB140MCASA20
30.6034 P14G9245 FD145T B-3622-13	43# M6915 610301-600 416820-133	2 1725 TEFC	230/3/60	NON-REV EN-23C10 REV. ER-23C10	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4361 6.3-10.0 AMP AB140MC2EC10	33.1911 AB1497N2PHYA	33.1691 AB140MCASA20
			460/3/60	NON-REV EN-46B40 REV. ER-46B40	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4321 2.5-4.0 AMP AB140MC2EB40	33.1912 AB1497N2PHYB	33.1691 AB140MCASA20

NOTE:

Each Magnetic Starter Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)