

**MAGNETIC STARTERS & TRANSFORMERS FOR
STANDARD HYTROL MOTORS**

FOOT MOUNTED 575 VOLT 3 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL.	MOTOR VOLTAGE MOTOR F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
30.2064 P56H1602 FB56 B-3622-13	23# M6976 610302-816 416820-133	1/2 1725 TENV	500/575 /3/60 0.96	NON-REVERSING EN-57B10 REVERSING ER-57B10	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4261 0.63 - 1.00 AMP AB140MC2EB10	33.1913 AB1497N3PHYC	33.1691 AB140MCASA20
30.3064 P56H1601 EC56 B-3622-13	26# M6905 610301-254 416820-133	3/4 1725 TEFC	500/575 /3/60 1.04	NON-REVERSING EN-57B16 REVERSING ER-57B16	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4281 1.00 - 1.60 AMP AB140C2EB16	33.1913 AB1497N3PHYC	33.1691 AB140MCASA20
30.4064 P56H1741 FB56 B-3622-13	27# M6906B 610301-567 416820-133	1 1725 TEFC	500/575 /3/60 1.36	NON-REVERSING EN-57B16 REVERSING ER-57B16	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4281 1.00 - 1.60 AMP AB140C2EB16	33.1913 AB1497N3PHYC	33.1691 AB140MCASA20
30.5064 P14H1702 FB145T B-3622-13	36# M2920AV 610301-600 416820-133	1 1/2 1725 TEFC	500/575 /3/60 2.2	NON-REVERSING EN-57B25 REVERSING ER-57B25	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4301 1.60 - 2.50 AMP AB140C2EB25	33.1913 AB1497N3PHYC	33.1691 AB140MCASA20
30.6064 P14H1701 FJ145T B-3622-13	40# M2916S 610301-600 416820-133	2 1725 TEFC	500/575 /3/60 2.6	NON-REVERSING EN-57B40 REVERSING ER-57B40	33.4101 AB103HNX1 33.4141 AB107HNX1	33.4321 2.50 - 4.00 AMP AB140C2EB40	33.1913 AB1497N3PHYC	33.1691 AB140MCASA20

NOTE:

Each Magnetic Starter Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)