

**MAGNETIC STARTERS & TRANSFORMERS (IF REQUIRED) FOR
STANDARD HYTROL MOTORS**

C - FACE 115 /230 VOLT 1 PHASE (1.15 S.F.)

MOTOR DATA				STARTER DATA				
HYTROL # RELIANCE # FRAME INSTR. MAN.	WEIGHT DATA SHT. DIM. SHT. CONN. DIA.	H.P. R.P.M. ENCL.	VOLTAGE F.L.AMPS	HYTROL STARTER ASSEMBLY #	CONTACTOR & ENCLOSURE HYTROL # ALLEN-BRADLEY #	MOTOR PROTECTOR HYTROL # CURRENT RANGE ALLEN-BRADLEY #	CONTROL CIRCUIT TRANSFORMER HYTROL # ALLEN-BRADLEY #	AUX CONTACT FOR POWER TO TRANSFORMER
30.7114 C56S1590 FB56C B-3622-13	27# M8275 610301-599 416820-30	1/2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	NOT	33.1691
			9	REV. ER-1SC10	33.4161 AB107HNX2	AB140MC2EC10	REQUIRED	AB140MCASA20
			230 / 1 / 60	NON-REV EN-2SB63	33.4121 AB103HNX2	33.4341 4.0-6.3 AMPS	33.1911	33.1691
			4.5	REV. ER-2SB63	33.4181 AB107HNX3	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20
30.7214 C56S1589 FB56C B-3622-13	34# M6983 610301-599 416820-30	3/4 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC16	33.4121 AB103HNX2	33.4381 10-16 AMPS	NOT	33.1691
			11	REV. ER-1SC16	33.4161 AB107HNX2	AB140C2EC16	REQUIRED	AB140MCASA20
			230 / 1 / 60	NON-REV EN-2SB63	33.4121 AB103HNX2	33.4341 4.0-6.3 AMPS	33.1911	33.1691
			5.5	REV. ER-2SB63	33.4181 AB107HNX3	AB140MC2EB63	AB1497N2PHYA	AB140MCASA20
30.7314 C56S1782 FC56C B-3622-13	34# M8274 610301-599 416820-30	1 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC16	33.4121 AB103HNX2	33.4381 10-16 AMPS	NOT	33.1691
			13.6	REV. ER-1SC16	33.4161 AB107HNX2	AB140C2EC16	REQUIRED	AB140MCASA20
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			6.8	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20
30.7414 C14H1515 FE145TC B-3622-13	51# M3145 610301-603 416820-30	1 1/2 1725 TEFC	115 / 1 / 60	NON-REV EN-1SC20	33.4121 AB103HNX2	33.4401 16-20 AMPS	NOT	33.1691
			16.0	REV. ER-1SC20	33.4161 AB107HNX2	AB140MC2EC20	REQUIRED	AB140MCASA20
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			8.0	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20
30.7514 C14H1516 FE145TC B-3622-13	55# M6626 610301-603 416820-30	2 1725 FEFC	115 / 1 / 60	NON-REV EN-1SC20	33.4121 AB103HNX2	33.4401 16-20 AMPS	NOT	33.1691
			16.0	REV. ER-1SC20	33.4161 AB107HNX2	AB140MC2EC20	REQUIRED	AB140MCASA20
			230 / 1 / 60	NON-REV EN-2SC10	33.4121 AB103HNX2	33.4361 6.3-10 AMPS	33.1911	33.1691
			8.0	REV. ER-2SC10	33.4181 AB107HNX3	AB140MC2EC10	AB1497N2PHYA	AB140MCASA20

NOTE:

Each Magnetic Starter (EXCEPT 115 VOLT) Shall Be Supplied, As Standard, With A Control Circuit Transformer,
NOT MOUNTED OR WIRED. (Unless Noted On The Order: Less Control Circuit Transformer, or mounted and wired)

